

## Yes, we have reinvented the Light Switch!

Light-Switch is a wall mounted DMX512 controller. Available in both UK and USA panel format, Light-Switch simply attaches to a standard conduit back box.

Control is provided by fourteen illuminated buttons. Four buttons, labelled A to D select a playback page. Eight buttons, labelled 1 to 8 initiate playback of a programmed show.

Overall grand master level is controlled using the arrow buttons.

Light-Switch controls all 512 channels available on the DMX512 output. For added flexibility, an infrared port is available. This is compatible with standard 'TV' style handsets.

The product is programmed using a Windows software package called Switch-Edit. Switch-Edit allows the show to be programmed live if required. The completed show is downloaded to Light-Switch and stored in a non-volatile flash drive. A moving lamp library is included.

Pages A to C access 24 memories with programmable fade time. Page D accesses 6 sequences with individual step times, stop & start and forward & reverse control.

### Specification:

- UK Dim: 85 x 146 x 30 mm
- US Dim: 114 x 162 x 30 mm
- Input voltage: 9 VDC
- Power: 2 W
- Power Con: Screw Terminal
- DMX Con: Screw Terminal
- Prog Con: Jaguar
- Listing: CE / FCC
- IP: Indoor use only



Light-Switch can also be programmed by snapshot of received DMX512. This allows any DMX512 console to programme Light-Switch.

Light-Switch also supports 'zones' for multi-room applications. Multiple Light-Switch units can be connected to a single DMX512 cable and configured such that each Light-Switch only controls specific channels.

The perfect solution for multi-room lighting.

### Power Supply (not included):

PSU-9-1.5-FER

- Input voltage: 100 - 230 VAC
- Output: 9V DC 1.5A
- Num. powered: 4
- Listing: CE / FCC / UL / PSE
- IP: Indoor use only